



Important Considerations and Restrictions

When more than one transformer is used in accordance with US National Electric Code Section 725-32 and table 725-31 (a) and control devices are operated by a common switch, connect the White low voltage secondary commons of both transformers by a common wire. Transformer primaries must be wired identically (correct polarity) to the same phase. Such installations are not permitted in Canada by Canadian Electric Code C22.1 subrule S 16-200 (4).

RPWRxxx

DESCRIPTION

The RPWRxxx is the power supply for the RINTERxx GE Lighting Automation Panel. The complete assembly consists of four modules:

1. Tub
2. Interior
3. Power Supply (RPWRxxx)
4. Cover

Features

1. Overcurrent protection. Transformer automatically goes off when overloaded and resets when fault is removed.
2. Two separate 40VA transformers. Separate transformers for relays and intelligence modules provides relay wiring flexibility while ensuring a stable power source for the electronic options.
3. GE-MOV voltage spike protection. Metal Oxide Varistors protect all downstream electronics from powerline voltage spikes.

SPECIFICATIONS

Description	Lighting Automation Panel Power Supply	
Catalog #	RPWRxxx	
Operating Environment	0-55 Degrees C (32-131 F) 0-95% RH, Non Condensing Non Corrosive atmosphere	
Catalog #	Weight	Voltage/Hz
RPWR115	6 lbs/2.7 Kg	115/50-60
RPWR220	6 lbs/2.7 Kg	220/50-60
RPWR240	6 lbs/2.7 Kg	240/50-60
RPWR277	6 lbs/2.7 Kg	277/50-60
RPWR347	6 lbs/2.7 Kg	347/50-60
Mounting	In RINTERxxx	
Codes	UL 916 Energy Management CSA Certified	

Job Name: _____	Page: ____ of ____